


TELEFUNKEN Partner 7281 T



Technical Data

Battery: 9 volt high efficiency battery for transistor sets, 1x1x1 1/2"

Feed Current: appr. 6 mA

Transistors: 8 - OC 614, OC 614, AF 105, AF 105, OC 602, OC 604, AC 105, AC 105

Germanium diodes: 2 with 3 functions, OA 174 local sender adjustment, OA 174 rectification and automatic volume control potentiol

Circuits: 5, 2 with variable condensor

Wave lengths: Middle wave: 515 - 1630 kc (583 - 184 m)
Short wave 2: 3 - 7,5 Mc (100 - 40 m)
Short wave 1: 9,4 - 18,2 Mc (31,8 - 16,5 m)

Antennas: telescopic antenna, movable, a built in frame onlenno for short wave, connection for exterior short wave ontenno, built in ferrite antenna for middle- ond short wave

Intermediate frequency: 460 kc

AVC: retroactive to the 1st IF stage

Volume control: logarithmic, combined with ON-OFF

Loudspeaker: 1 permanent dynamic loudspeaker 2 3/4" Voice coil impedance, 10 Ohms

Output capacity: appr. 180 mW

Earphone socket: for miniature earphone, impedonce 10-100 ohms

Case: Polystyral (shock proof synthetic) beige/red, grey/charcoal, or grey/turquoise

Dimensions: 6 3/4" x 3 3/4" x 1 1/4"

Weight: without battery 1 lb 3 1/2 oz.
with battery 1 lb 4 1/2 oz.

The receiver is tropicalized.

